



THIS PAGE IS OUT OF DATE. PLEASE MOVE ON TO [eunhasu](#) PAGE.

User Guide

The SMS-200's formal operating instruction is available in <http://sotm-audio.com>.

sMS-200 is a compact designed high performance network file player which is capable to share and play music file through network system. You can simply set up the multi-room network audio system by connecting a USB audio device to the special USB audio port on the rear panel of sMS-200.

- **Roon Ready:** Roon Ready is the easy and user friendly network music file player working with Roon Server, it provides the most powerful music playback function.
- **Squeezelite:** Squeezelite is a network music file player working with Logitech Media Server, it is integrated with versatile services such as Tidal, Qobuz or internet radios.
- **MPD & DLNA:** MPD is a music file player supports playing the music file saved on USB storage device or network share folder. And DLNA is a DLNA audio renderer working with DLNA server and DLNA control point throughout MPD function.
- **HQPlayer NAA:** High quality music playback via [HQPlayer Desktop](#) in local network.
- **Shairport:** Shairport is an AirPlay audio player but it does not support AirPlay video or photo streaming.


How to use

1. Connect a USB audio device to the High-End audio grade USB port on sMS-200 by USB cable.
2. Connect a network router to the Ethernet port on sMS-200 by Ethernet cable.
3. Check operating status of the server, each server device should operate normally in the local area network. e.g.
 - Roon Ready: The device which is running ROON server should be operated normally in the same local network.
 - SqueezeLite or MPD: connect the USB storage device to the USB 2.0 port on the rear panel of sMS-200 or setup a network music folder path on Library config page.
 - DLNA: connect sMS-200 to a DLNA server by a DLNA control point.
 - HQPlayer NAA: start NAA and select output audio in [HQPlayer Desktop](#) setting menu.
 - Shairport: start Shairport service and change your iPhone or iDevice's output direction in an app.
4. Turn on sMS-200 by connecting the correct power supply to POWER IN jack on the rear panel of sMS-200.
5. Wait around less 30 seconds until the sMS-200 boot process is completed and then type <http://eunhasu/> or its own IP address on a web browser to connect Eunhasu GUI. You can get Eunhasu device's IP address or link from <http://sotm-audio.com/my> if you're using Android device. <http://sotm-audio.com/my> site is working based on IPv4 network. Type <http://eunhasu.local> for iOS.
6. Once connected sMS-200 Web Page, Eunhasu, select one of audio function icons which you wish to use.
7. Touch or mouse over one of audio function icons, you will see there are action buttons () available.


8. Click 'Start' button to make the function activated and it will need around less 10 seconds to be applied and then 'Active' sign will be shown under the icon.
9. If you want to change the audio function, click 'Stop' button on the current audio function and change the audio function using the above procedure.
10. To turn off the sMS-200, click the System power off button on the System setup icon.

Video clips


Roon ready on SMS-200



Squeezelite on SMS-200



HQplayer on SMS-200



From:

<https://docs.sotm-audio.com/> - **SOtM docs**

Permanent link:

https://docs.sotm-audio.com/doku.php?id=en:sms-200_user_guide

Last update: **2017/09/25 23:45**

