

Another upgrade process

## By samba

1. Download upgrade-last.tar file from server
  - [SMS-200](#)
  - [SMS-1000SQ](#)
2. Copy upgrade-last.tar to Eunhasu samba directory `\\eunhasu\mw\data\music`
3. Eunhasu page load like [http://eunhasu/upgrade.php?upgrade\\_server=eunhasu/music&force=1](http://eunhasu/upgrade.php?upgrade_server=eunhasu/music&force=1)
  1. `upgrade_server={EUNHASU_IP}/music` is possible

## By USB

1. Format USB to FAT32
2. Change USB label to SOTMDEBUG and it must upper case
3. Download upgrade-last.tar file from server
  - [SMS-200](#)
  - [SMS-1000SQ](#)
4. Copy downloaded upgrade-last.tar to the USB root directory
5. Make file named run\_debug.txt in the USB
6. run\_debug.txt file must contain following strings

upgrade force

## By external utility

[Refer Here](#)

From:  
<https://docs.sotm-audio.com/> - **SOTM docs**

Permanent link:  
[https://docs.sotm-audio.com/doku.php?id=en:how\\_to\\_upgrade\\_another\\_way&rev=1481010598](https://docs.sotm-audio.com/doku.php?id=en:how_to_upgrade_another_way&rev=1481010598)

Last update: **2016/12/06 02:49**

