

This document describes another upgrade instruction for Eunhasu.

By samba share

1. Download upgrade-last.tar file from server
 - [SMS-200](#)
2. Copy upgrade-last.tar to Eunhasu samba directory `\\eunhasu\mw\data\music`
3. Eunhasu page load like http://eunhasu/upgrade.php?upgrade_server=eunhasu/music&force=1
 1. `upgrade_server={EUNHASU_IP}/music` is possible

By USB

1. Format USB to FAT32
2. Change USB label to SOTMDEBUG and it must upper case
3. Download upgrade-last.tar file from server
 - [SMS-200](#)
4. Copy downloaded upgrade-last.tar to the USB root directory
5. Make file named run_debug.txt in the USB
6. run_debug.txt file must contain following strings

```
upgrade force
```

7. Remove whole inserted USB stick on SMS-200
8. Insert SOTMDEBUG USB to SMS-200
9. On working, blinking left LED
10. After finish, device shows left LED off

By external utility

- SMS-200 - [Refer Here](#)

From:

<https://docs.sotm-audio.com/> - **SOTM docs**

Permanent link:

https://docs.sotm-audio.com/doku.php?id=en:how_to_upgrade_another_way&rev=1481011361

Last update: **2016/12/06 03:02**

